



CHARGING & DISCHARGING POWER

UP TO 9 KW EVEN IN FULL BACKUP POWER MODE

MAXIMUM CHARGING AND DISCHARGING POWER WITH GEN24 PLUS (KW)	HVS 5.1	HVS 7.7	HVS 10.2	HVM 11.0	HVM 13.8	HVM 16.6	HVM 19.3	HVM 22.1
Primo GEN24 3.0 Plus	3.13	3.13	-	3.13	3.13	3.13	3.13	-
Primo GEN24 3.6 Plus	3.81	3.81	-	3.81	3.81	3.81	3.81	-
Primo GEN24 4.0 Plus	4.14	4.14	-	4.14	4.14	4.14	4.14	-
Primo GEN24 4.6 Plus	4.51	4.75	-	4.51	4.75	4.75	4.75	-
Primo GEN24 5.0 Plus	4.51	5.17	-	4.51	5.17	5.17	5.17	-
Primo GEN24 6.0 Plus	4.51	6.20	-	4.51	5.63	6.20	6.20	-
Symo GEN24 3.0 Plus	2.56	3.13	3.13	2.56	3.13	3.13	3.13	3.13
Symo GEN24 4.0 Plus	2.56	3.84	4.17	2.56	3.20	3.84	4.17	4.17
Symo GEN24 5.0 Plus	2.56	3.84	5.12	2.56	3.20	3.84	4.48	5.12
Symo GEN24 6.0 Plus	4.51	6.22	6.22	4.51	5.63	6.22	6.22	6.22
Symo GEN24 8.0 Plus	4.51	6.76	8.26	4.51	5.63	6.76	7.88	8.26
Symo GEN24 10.0 Plus	4.51	6.76	9.01	4.51	5.63	6.76	7.88	9.01